



GUJARAT TECHNOLOGICAL UNIVERSITY

BE - SEMESTER- III EXAMINATION – SUMMER 2020

Subject Code: 3131705

Date: 27/10/2020

Subject Name: Dynamics of Linear Systems

Time: 02:30 PM TO 05:00 PM

Total Marks: 70

Instructions:

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

		Marks
Q.1	(a) Explain continuous-time and discrete-time signals with suitable example.	03
	(b) For each of the following input-output relationships, determine whether the corresponding system is linear, time invariant or both. 1. $y(t) = t^2 x(t-1)$ 2. $y[n] = x[n+1] - x[n-1]$	04
	(c) What is time-variant and time-invariant system? Determine causality and stability of the following discrete-time systems with justification. Consider $y[n]$ is the system output and $x[n]$ is the system input. 1. $y[n] = x[-n]$ 2. $y[n] = x[n-2] - 2x[n-8]$	07
Q.2	(a) Explain LTI systems with and without memory.	03
	(b) A linear time-invariant system is characterized by its impulse response $h[n] = \left(\frac{1}{2}\right)^n u(n)$. Determine energy density spectrum of the output signal when the system is excited by the signal $x[n] = \left(\frac{1}{4}\right)^n u(n)$.	04
	(c) Compute and plot the convolution $y[n] = x[n] * h[n]$, where $x[n] = \left(\frac{1}{3}\right)^n$ and $h[n] = u[n-1]$.	07
	OR	
	(c) Explain commutative and distributive property of a LTI system.	07
Q.3	(a) For $x(t) = 1 + \sin w_0 t + 2 \cos w_0 t + \cos\left(2w_0 t + \frac{\pi}{4}\right)$. Determine Fourier series coefficient using complex exponential representation.	03
	(b) Discuss applications of frequency-selective filters.	04
	(c) Discuss the properties of continuous-time Fourier series.	07

OR

- Q.3 (a)** Each of the two sequences $x_1[n]$ and $x_2[n]$ has a period $N = 4$, and the corresponding Fourier series coefficients are specified as $x_1[n] \longleftrightarrow a_k$ and $x_2[n] \longleftrightarrow b_k$ **03**

Where,

$a_0 = a_3 = \frac{1}{2} a_1 = \frac{1}{2} a_2 = 1$ and $b_0 = b_1 = b_2 = b_3 = 1$. Using the multiplication property, determine the Fourier series coefficients c_k for the signal $g[n] = x_1[n] x_2[n]$.

- (b)** Discuss applications of frequency-shaping filters. **04**
 Determine whether each of the following statements is true or false. Justify your answers. **07**
1. An odd and imaginary signal always has an odd and imaginary Fourier transform.
 2. The convolution of an odd Fourier transform with an even Fourier transform is always odd.

- Q.4 (a)** Explain time reversal and linearity property for the discrete time Fourier transforms. **03**

- (b)** Determine the Fourier transform for $-\pi \leq \omega < \pi$ for the periodic signal $x(n) = \sin\left(\frac{\pi}{3}n + \frac{\pi}{4}\right)$. **04**

- (c)** Consider a discrete-time LTI system with impulse response $h(n) = \left(\frac{1}{2}\right)^n u(n)$. **07**

Use Fourier transforms to determine the response for the input

$$x(n) = \left(\frac{3}{4}\right)^n u(n).$$

OR

- Q.4 (a)** Explain differentiation and integration property for the continuous time Fourier transforms. **03**

- (b)** Determine the Fourier transform of periodic signal $x(t) = 1 + \cos\left(6\pi t + \frac{\pi}{8}\right)$. **04**

- (c)** Compute the Fourier transform of each of the following signals: **07**

$$1. \quad x[n] = u[n-2] - u[n-6]$$

$$2. \quad x[n] = \left(\frac{1}{2}\right)^{-n} u[-n-1]$$

- Q.5 (a)** Determine the Laplace transform and the associated region of convergence for $x(t) = e^{-2t}u(t) + e^{-3t}u(t)$. **03**

- (b)** Determine the function of time $x(t)$, for the following Laplace transforms and their associated regions of convergence: **04**

$$\frac{1}{s^2 + 9}, \quad \Re\{s\} > 0.$$

- (c)** Explain properties of the Z-transform. **07**

OR

Q.5 (a) Find Z-transform and region of convergence of **03**

$$x(n) = 7\left(\frac{1}{3}\right)^n u(n) - 6\left(\frac{1}{2}\right)^n u(n).$$

(b) Find inverse Z-transform for $X(z) = \log(1 + az^{-1})$, $|z| > |a|$. **04**

(c) Consider the system function corresponding to causal LTI **07**

$$\text{systems: } H(z) = \frac{1}{(1 - z^{-1} + \frac{1}{4}z^{-2})(1 - \frac{2}{3}z^{-1} + \frac{1}{9}z^{-2})}.$$

1. Draw a direct-form block diagram.
2. Draw a block diagram that corresponds to the cascade connection of two second-order block diagrams. Each second-order block diagram should be in direct form.

firstranker.com
www.FirstRanker.com