

Printed Pages: 4

NEC-702(A)

(Following Paper ID and Roll No. to be filled in your Answer Books)

Paper ID : 2295034

Roll No.

--	--	--	--	--	--	--	--	--	--

B.TECH

Regular Theory Examination (Odd Sem - VII), 2016-17

ANALOG & DIGITAL COMM.

Time : 3 Hours

Max. Marks : 100

SECTION - A

1. Attempt all 10 parts from the following : (10×2=20)

- Draw the Basic block diagram of analog communication system.
- Determine the pulse transmission rate in terms of transmission bandwidth B_T and the roll off factor r . Assume a scheme using Nyquist First Criteria?
- Which passband modulation can't be detected using non coherent technique? What is the reason for this?
- Define Modulation and explain the need of Modulation?
- What is the purpose of multiplexing?
- Explain the difference between TDM & FDM.
- Giving the drawbacks of DSB-SC, explain the need of SSB-SC.
- What is Kraft Inequality?

NEC-702(A)

- (i) What is frequency deviation and explain the Carson's rule.
- (j) An analog signal is bandlimited to 4 KHz. It is sampled at the Nyquist rate and the samples are quantized into 4 levels. The quantization levels are independent messages having probability $P_1 = P_2 = 1/8$ and $P_3 = P_4 = 3/8$. Find the information rate of the source.

SECTION - B

2. Attempt any 5 parts from the following 8 parts :
(5×10=50)

- a) Explain Multiplexing concept and then explain T-1 carrier multiplexing scheme. Draw the TDM hierarchy and write down the bit rate at each multiplexing stage.
- b) Consider 8 alphabet source with probability of occurrence as follows :

Symbol (xi) A B C D E F G H

Probability [p(xi)] .30 .20 .15 .12 .10 .07 .04 .02

According to Shannon - Fano techniques, generate the binary codes.

- c) Differentiate between TRF receiver and Super heterodyne receiver. What are the functions of receiver?
- d) Draw and explain Envelope Detector circuit for demodulation of AM signal along with the appropriate Time Constant range.

NEC-702(A)

- e) i) A 400W carrier is amplitude modulated to a depth of 100%. Calculate the total power in case of AM and DSB-SC technique. How much power saving is achieved for DSBSC. If depth of modulation is changed to 75% then how much power is required for transmitting DSBSC wave.

- ii) A SSB transmitter radiated 0.5KW when the modulation percentage is 60%. How much of carrier power is required if we want to transmit the same message by an AM transmitter.

- f) Explain the working of Quadrature Phase Shift Keying with transmitter and receiver. Draw the constellation diagram and phase diagram. Drive the Probability of error for the same.

- g) i) Draw and explain the block diagram of transmitter and receiver of DPCM.

- ii) Consider a sinusoidal signal $m(t) = A \cos \omega_m t$ applied to a delta modulator with step size Δ . Explain the condition when delta modulator avoids slope overload distortion.

NEC-702(A)

b) Determine the Huffman code for the following message with their probabilities given:

x	x1	x2	x3	x4	x5	x6	x7
P	0.05	0.15	0.2	0.05	0.15	0.3	0.1

Also calculate the entropy, redundancy and efficiency of the codes generated.

SECTION -C

Note : Attempt any 2 parts from the following 3 parts:

(2×15=30)

3. i) Using block diagram, explain generation and detection of DPSK system for data $d(t) = 0\ 1\ 1\ 0\ 1$ and also draw the waveform.
- ii) Explain bit interleaving.
4. i) With the help of block diagram explain the working of Delta modulation. How Adaptive Delta modulator improves the performance of Delta modulator?
- ii) Explain different type of internal and external noises.
5. i) Explain the generation and detection of FSK.
- ii) Give the comparison details of ASK, FSK and PSK.

