FirstRanker.com

www.FirstRanker.com

	USN	14ELE15/25	
	First/ Second Semester B.E. Degree Examination, June/July 2015 Basic Electrical Engineering		
	Tin	ne: 3 hrs. Max. Marks:lab Note: Answer any FIVE full questions, ite selecting ONE full question from each part. cz	
tice.		PART-1	
ıe remaining blank pages. en eg, 42+8 = 50, will be treated as malprac	1	a. State and explain Faraday's laws of electromagnetic induction. ( (06 Marks) b. An air cored solenoid has a length of 50 cm and a diameter inductances if it has 1000 turns and also find the energy stored in in Nie current rises from zero to 5A. c. If the total power dissipated in the circuit shown is 18W, c!'the value of 'R.' and its current. OA. cf';:r4. (08 Marks)	
	2	fig.Q1(c) a. State the following: i) Fleming's right hand ii) Fleming's left han iii) Flem	
0	3 a	<ul> <li>a. Explain the characteristics of DC series motor with a neat diagram. (06 Marks)</li> <li>b. Explain the significance of back emf in DC motor. (05 Marks)</li> <li>c. 4 pole DC shunt motor takes 22.5A from a 250V supply, R a = 0.50 and R5h = 1255. The armature is wave wound with 300 conductors. If the flux per pole is 0.02wb. Calculate : <ul> <li>i) speed</li> </ul> </li> </ul>	
		ii) torque developed iii) power developed. (09 Marks) 1 of 2	

FirstRanker.com

www.FirstRanker.com

www.FirstRanker.com

## 14ELE15/25

(06 Marks)

(04 Marks)

- a. With a neat diagram, explain the construction and working of dynamo-meter type wattmeter. 4 (06 Marks)
  - b. A 4 pole generator with wave wound armature has 51 slots, each having 24 conductors. The flux per pole is 0.01 wb. At what speed must the armature rotate to give an induced emf of 220V? What will be the voltage developed if the winding is lap and the armature rotates at the same speed. (10 Marks)
  - Explain with a diagram, the construction features of various parts of aDC generator. (04 Mael) c.

## PART-3

- a. What is meant by power factor in AC circuit? What is its significance in A C circ 5 46 Marks)
  - **b.** Draw and explain the wiring diagram for the 3 way control of lamp.
  - c. A series circuit with resistance of 10 S2, inductance of 0.2H and cap ice of 40 .tF is supplied with a 100 V supply at 50 Hz. Find the current, power ewer factor of the (08 Marks) circuit.

a. State form factor of an alternating quantity. Derive the expres st or it. (08 Marks) 6

- b. Show that the average power consumed in a pure ca tltnce is zero. Draw the neat waveform for voltage, current, power. (06 Marks) (06 Marks)
- With a neat diagram, explain pipe earthing. c.

## PARTN.

- a. With the usual notation, derive the expressioEg\_trlsifF equation of an alternator. (06 Marks) 7 b. Establish the relationship between phase areiine values of voltage and currents in 3 phase
  - delta connected circuit. Show the phas diagram neatly. (06 Marks) c. A balanced star connected load o ) Wphase is connected to 3 phase, 230V supply. r reactive volt-ampere and total volt-ampere. (08 Marks) Find the line current, power facto
- a. Show that the power in a bal ...d 3 phase circuit can be measured by 2 wattmeters. Draw 8 the circuit and vector dia (08 Marks)
  - **t.** Explain the generation phase AC voltage.
  - c. A 3 phase, 50 Hr, pole generator with star connected winding has 144 slots with
  - conductor /slot i/32fIlie flux per pole is 24.8 m wb is sinusiodally distributed. The coils are full pitched. ktiti-T i) speed ii) the line emf. (08 Marks) (N\$) \* ····

## PART-5

- a. Exp e construction and working principle of a transformer with a neat sketch.(08 Marks) 9
  - **b.** E the concept of rotating magnetic field in a 34) induction motor. (06 Marks) equency of the emf in the stator of a 4 pole induction motor is 50 Hz and in the rotor is c. GO'S Hz. What is the slip and at what speed is the motor running? (06 Marks)

a' What is 'slip' in an induction motor? Explain why slip is never zero in an induction motor. (06 Marks)

- b. A single phase transformer has 400 turns primary and 1000 secondary turns. The net cross — sectional area of the core is 60 cm  $^2$ . The primary winding is connected to a 500V, 50 Hz supply. Find :
  - i) Peak value of flux density
  - ii) emf induced in the secondary winding.
- c. The maximum efficiency at full load and unity p.f. of a single phase 25 KVA, 500/1000V, 50Hz transformer is 98%. Determine its efficiency at
  - i) 75% load, 0.9 p.f. and
  - ii) 50% load, 0.8 p.f.

(08 Marks)

(06 Marks)