



Roll No.

--	--	--	--	--	--	--	--	--	--

Total No. of Pages : 02

Total No. of Questions : 8

M.Tech. (EE) (2018 Batch) (Sem.-2)

**ADVANCED DIGITAL SIGNAL PROCESSING**

Subject Code : MTEE-203B-18

M.Code : 76103

Time : 3 Hrs.

Max. Marks : 60

**INSTRUCTIONS TO CANDIDATES :**

1. Attempt any FIVE questions out of EIGHT questions.

2. Each question carries TWELVE marks.

- Determine the correct classification of the system with proper justification
  - $y(n) = 2x(n) + 3$  in terms of linear or nonlinear,
  - $y(n) = x(n+1) + \frac{x(n)}{x(n-1)}$  in terms of causal or not causal,
  - $y(n) = 3nx(n)$  in terms of time variant or time invariant,
  - $h(n) = 4^n u(-n)$  in terms of stable or not stable.
- State the property of differentiation in Z-domain. Also find Z-transform of the sequence  $x(n) = (n+0.5)\left(\frac{1}{3}\right)^n u(n)$ .
- Input  $x(n] = \{1, 2, 3, 1\}$  and Impulse response  $h(n) = \{1, 1, 1\}$  of a LTI system. Determine the response of the system by calculating linear convolution using circular convolution.
- Design a discrete time Butterworth filter for the following specifications using an impulse invariant method

$$0.8 \leq |H(e^{j\omega})| \leq 1 \quad \text{for} \quad 0 \leq \omega \leq 0.2\pi$$

$$|H(e^{j\omega})| \leq 0.2 \quad \text{for} \quad 0.6\pi \leq \omega \leq \pi. \text{ The sampling frequency is 1Hz.}$$



5. Design a low pass FIR filter with a cutoff frequency of 0.25 kHz and a sampling frequency of 1 kHz using Hanning window. Assume a filter length  $N = 11$ . Find its windowed causal impulse response sequence and transfer function  $H(z)$  of the causal filter.
6. What are overflow oscillations and zero input limit cycle oscillations in IIR filters? Explain each using a suitable example.
7. Describe all poles and all zeros model. Also provide the estimation of power spectrum of stationary random signals.
8. Write short notes on :
  - a) Optimum signal estimation
  - b) Mean square error estimation.

**NOTE : Disclosure of Identity by writing Mobile No. or Making of passing request on any page of Answer Sheet will lead to UMC against the Student.**