www.FirstRanker.com

Roll No.

Paper ID:1002

B.Tech.

(SEM III) THEORY EXAMINATION 2017-18 Discrete Structures & Theory of Logic

Time: 3 Hours

Note: 1. Attempt all Sections. If require any missing data; then choose suitably. Any special paper specific instruction.

SECTION A

1. Attempt all questions in brief.

- Define Eulerian path, circuit and graph
- b. Let A=(2,4,5,7,8)=B ,aRb if and only if a+b<=12.Find relation matrix
- c. Explain edge coloring and k egde coloring.
- d. Define Chromatic number and Isomorphic graph.
- e. Define union and intertersection of multiset and find for A=[1,1,4,2,2,3],B=[1,2,2,6,3,3].
- f. Find the contrapositive of -"If he has courage, then he will win".
- g .Define rings and write its properties.

SECTION I

2. Attempt any three of the following:

- Prove by mathematical induction $3+33+333+.....33..3 = (10^{n+2}9n-10)/27$
- b. Define the following with one example: i) Bipartite graph.
 - ii) Complete graph.
 - iii) How many edges in K7 and K3.6
 - iv) Planar Graph.

FirstRanker.com

Firstranker's choice

c. For any positive integer D36, then find whether (D36,']') is lattice or not?

- d. Let X={1,2,3.....7} and R={(x,y) | (x-y) is divisible by 3). Is R equivalence relation Draw the diagraph of R
- e. Simplify the following Boolean function using K-map: $F(x,y,z)=\sum_{x}(0,2,3,7)$

 $2 \ge 7 = 14$

 $7 \ge 3 = 21$

www.FirstRanker.com

www.FirstRanker.com Sub Code: RCS 301

Total Marks: 70

FirstRanker.com

Printed pages:2

FirstRanker.com www.FirstRanker.com SECTION C

3. Attempt any one part of the following:

- (a) Solve $a_r-6a_{r-1}+8a_{r-2}=r.4^r$, given $a_0=8$, and $a_1=1$.
- (b) Show that: $r \rightarrow \neg q$, $r \lor s$, $s \rightarrow \neg q$, $p \rightarrow q \leftrightarrow \neg p$ are inconsistent

4. Attempt any one part of the following:

- (a) Write the properties of Group. Show that the set(1,2,3,4,5) is not group under addition and multiplication modulo 6.
- (b) Prove by mathematical induction

 n^4 -4 n^2 is divisible by 3 for all $n \ge 2$.

5. Attempt any one part of the following:

(a)Explain Modular lattice, distribute lattice and bounded lattice with eg and diagram

(b) Draw the Hasse diagram of (A, ≤), where

A= $\{3,4,12,24,48,72\}$ and relation \leq be such that a \leq b if a divides b

Attempt any one part of the following: 6.

 Given the inorder and postorder traversal of a tree T Inorder : HFEABIGDC Postorder : BEHFACDGL

Determine the tree T and its Preorder.

- (b) Translate the following sentences in quantified expressions of predicate logic.
 - i) All students need financial aid.
 - ii) Some cows are not white ...
 - iii) Suresh will get if division if and only if he gets first div.
 - iv) if water is hot, then shyam will swim in pool.
 - v) All integer are either even or odd integer.

Attempt any one part of the following: 7.

- (a) Define and Explain any two the following:
 - 1. BFS and DFS in Trees.
 - 2. Euler Graph

FirstRanker.com

Firstranker's choice

3. Adjacency matrix of a graph.

(b) Solve the recurrence relation: $\mathbf{a}_r + 4\mathbf{a}_{r,1} + 4\mathbf{a}_{r,2} = \mathbf{r}^2$.

www.FirstRanker.com



www.FirstRanker.com

 $7 \ge 1 = 7$

 $7 \ge 1 = 7$

 $7 \ge 1 = 7$

 $7 \ge 1 = 7$