

(Following Paper ID and Roll No. to be filled in your Answer Books)

Paper ID : 131661

Roll No.

**B.TECH.****Theory Examination (Semester-VI) 2015-16****DIGITAL SIGNAL PROCESSING****Time : 3 Hours****Max. Marks : 100****Section-A**

1. **Attempt all parts. All parts carry equal marks. Write answer of each part in short.** (2×10 = 20)

- What is Discrete Time Fourier Transform and How it is related to Discrete Fourier Transform?
- Establish the relation between Z-transform and DFT.
- What is zero padding? What are its uses?
- Calculate number of multiplications needed in calculation of DFT and FFT of 32 point sequence and also calculate speed improvement factor.
- Explain Bit- reversal and In-place computation.

(1)

P.T.O.

206/312/240/6000

Obtain Cascade realization with minimum number of multipliers.

- (i) What is Spectral leakage? Give remedy to this problem.
- (j) What are the main disadvantages of designing IIR filters using windowing technique?

**Section-B**

**Attempt any five questions from this section. (10×5=50)**

- (a) Find the 10-point DFT of the following sequences:
- $x(n) = \delta(n) + \delta(n-5)$
  - $x(n) = u(n) - u(n-6)$

(2)

206/312/240/6000

$$x(n) = \cos \frac{n\pi}{2}$$

- (ii) Show that the same algorithm can be used to compute IDFT of  $X(k)$  calculated in part (a).

- (d) Compute the DFT of following 8-point sequence using 4-point Radix-2 DIT algorithm.

$$x(n) = \{2, 2, 2, 2, 1, 1, 1, 1\}$$

- (e) Obtain Direct Form I, Direct Form II and Parallel Form structures for the following filter

$$y(h) = \frac{3}{4}y(h-1) + \frac{3}{32}y(h-2) + \frac{1}{64}y(h-3) + x(h) + 3x(h-1) + 2x(h-2)$$

(3)

206/312/240/6000

P.T.O.

- (a) Direct form II
- (b) A cascade of first-order and second-order system realized in transposed DF II
- (c) A Parallel connection of first-order and second-order systems realized in DF II (2+4+4)
- (g) A filter is to be designed with the following desired frequency response:

$$H_d(e^{jw}) = \begin{cases} 0 & -\Pi \leq w \leq \frac{\Pi}{4} \\ e^{-j2w} & \frac{\Pi}{4} \leq w \leq \Pi \end{cases}$$

- (h) Transform the prototype LPF with system function

$$H_{LP}(s) = \frac{\Omega_p}{s + \Omega_p} \text{ into a}$$

(4)

6/312/240/6000

3. (a) Prove that multiplication of the DFTs of two sequences is equivalent to the circular convolution of the two sequences in the time domain.

- (b) If the 10-point DFT of  $x(n) = \delta(n) - \delta(n-1)$  and  $h(n) = u(n) - u(n-10)$  are  $X(k)$  and  $H(k)$  respectively, find the sequence  $w(n)$  that corresponds to the 10-point inverse DFT of the product  $H(k)X(k)$ . (7+8)

4. (a) (i) Compute 4-point DFT of the following sequence using linear transformation matrix

$$x(n) = (1, 1-2, -2)$$

- (ii) Find IDFT  $x(n)$  from  $X(k)$  calculated in part(i). (2.5×2=05)

(5)

206/312/240/6000

P.T.O.



5. (a) An FIR filter has following symmetry in the impulse response:

$$h(n) = h(M - 1 - n) \text{ for } M \text{ odd.}$$

Derive its frequency response and show that it has linear phase.

- (b) Discuss the Bilinear Transformation method of converting analog IIR filter into digital IIR filter. What is Frequency Warping? (7+8)

(6)

206/312/240/6000