

[Contd...]

1

131602]

[ 13825 ]

$$H(z) = \frac{(1+z^{-1} + \frac{1}{2}z^{-2})(1+\frac{1}{2}z^{-1} + \frac{1}{2}z^{-2})}{(1+\frac{3}{2}z^{-1} + \frac{1}{2}z^{-2})(1-\frac{3}{2}z^{-1} + z^{-2})}$$

systems.

(b) Obtain the cascade realization for the following

$$y(n) + \frac{4}{1} y(n-1) = w(n)$$

$$w(n) = x(n) + \frac{2}{1} x(n-1) \text{ and}$$

with input  $x(n)$  and output  $y(n)$

(a) Draw the block diagram for the following system

1 Attempt any four parts      5x4=20

Total Marks : 100      Time : 3 Hours ]

### DIGITAL SIGNAL PROCESSING

(SEM. VI) THEORY EXAMINATION, 2014-15

B. Tech.

|   |         |
|---|---------|
| EEC602  | 10x2=20 |
| Following Paper ID and Roll No. to be filled in your Answer Book<br><b>PAPER ID : 131602</b>  |         |
| Roll No. <input type="text"/> |         |
|   |         |
| Printed Pages : 4   |         |

www.FirstRanker.com

- (c) Calculate the DFT of the sequence  
 $s(n)=\{2,4,2,3\}$ .

(d) State and prove circular convolution property of DFT.

(e) Explain frequency transformation with LPF to HPF conversion formula.

(f) Draw a transformation matrix of size  $5 \times 5$  and explain the properties of twiddle factor.

$$5 \times 4 = 20$$

Attempt any four parts

(a) Determine  $H(z)$  using the impulse invariant technique for the analog system function

$$H(s) = \frac{1}{(s+0.5)(s^2 + 0.5s + 2)}$$

(b) Realise an FIR filter whose impulse response is  $h(n)=\{1, 2, 5, 6, 3, 6, 5, 2, 1\}$  using minimum number of multipliers.

(c) Determine the response of a discrete-time system for an input signal  $s(n)=\{2,1,3,1\}$ , if the unit-sample response is of the system is  $h(n)=\{1, 2, 2, -1\}$

(d) Enumerate and explain the properties of DFT.  
 (e) Draw the parallel form network structure of the system with transfer function.

$$H(z) = \frac{2z(z+3)}{z^2 + 0.3z + 0.02}$$

(f) What are the different window functions used for windowing? Explain the effects of using different window functions for designing FIR filter on the filter response.

**3**  $10 \times 2 = 20$   
 Attempt any two parts

(a) Derive and draw the flow graph for DIF FFT algorithm for  $N=8$ .

(b) Calculate the circular convolution of  $s_1(n)=\{1,2,1,2\}$  and  $s_2(n)=\{1, 2, 3, 4\}$  using Stockham's method.

(c) Determine  $H(z)$  for a butterworth filter satisfying the following constraints

$$\sqrt{0.5} \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq \frac{\pi}{2}$$

$$|H(e^{j\omega})| \leq 0.2 \quad \frac{3\pi}{4} \leq \omega \leq \pi$$

with  $T=1$  sec. Apply impulse invariant transformation

$$10 \times 2 = 20$$

4 Attempt any two parts;

(a) Given  $x(n)=2^n$  and  $N=8$  find  $X(K)$  using DIT FFT algorithm. Also calculate the computational reduction factor.

(b) Design a low-pass filter with the following desired frequency response

$$H_d(e^{j\omega}) = \begin{cases} e^{-j2\omega}, & -\frac{\pi}{4} \leq \omega \leq \frac{\pi}{4} \\ 0, & \frac{\pi}{4} < |\omega| < \pi \end{cases}$$

and using window function

$$w(n) = \begin{cases} 1, & 0 \leq n \leq 4 \\ 0, & \text{otherwise} \end{cases}$$

- (c) Draw the Ladder structure for the system with system function

$$H(z) = \frac{5z^{-3} + 2z^{-2} + 3z^{-1} + 1}{z^{-3} + z^{-2} + z^{-1} + 1}$$

**5** Attempt any two parts : **10×2=20**

- (a) Design a digital chebyshev filter to satisfy the constraints

$$0.77 \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq 0.2\pi$$

$$|H(e^{j\omega})| \leq 0.1 \quad 0.5\pi \leq \omega \leq \pi$$

Using bilinear transformation with T=1s

- (b) Convert the analog filter with system function

$$H(s) = \frac{s+0.1}{(s+0.1)^2 + 9} \text{ into digital filter with a}$$

resonant frequency of  $\omega_r = \frac{\pi}{4}$  of using bilinear transformation.

- (c) Explain the following phenomenon's :

- (i) Gibbs Oscillations.
- (ii) Frequency Wrapping.

**Printed Pages : 4**



(Following Paper ID and Roll No. to)

**PAPER ID : 131602**

Roll No.

**B. Tech**

(SEM. VI) THEORY EXAMINATIONS

DIGITAL SIGNAL PROCESSING

Time : 3 Hours]

**1** Attempt any four parts

- (a) Draw the block diagram with input x(n) and output y(n).

$$w(n) = x(n) + \frac{1}{2}x(n-1)$$

$$y(n) + \frac{1}{4}y(n-1) = w(n)$$

- (b) Obtain the cascade realization of the system;

$$H(z) = \frac{(1+\frac{3}{2}z^{-1}+\frac{1}{2}z^{-2})(1+z^{-1}+\frac{1}{4}z^{-2})}{(1-z^{-1})(1-\frac{1}{2}z^{-1})^2}$$

**131602]**

**4**

**[ 13825 ]**

**131602]**

**1**

www.FirstRanker.com