

[Contd...

1

131602]

[13825]

$$H(z) = \frac{(1+z^{-1}+\frac{1}{4}z^{-2})(1+\frac{1}{2}z^{-1}+\frac{1}{4}z^{-2})}{(1+\frac{3}{2}z^{-1}+\frac{1}{2}z^{-2})(1-\frac{3}{2}z^{-1}+\frac{1}{2}z^{-2})}$$

system.

(b) Obtain the cascade realization for the following

$$y(n) + \frac{1}{4}y(n-1) = w(n)$$

$$w(n) = x(n) + \frac{1}{2}x(n-1) \text{ and}$$

 with input $x(n)$ and output $y(n)$

(a) Draw the block diagram for the following system

5×4=20

1 Attempt any four parts

[Total Marks : 100]

Time : 3Hours

B. Tech.
(SEM. VI) THEORY EXAMINATION, 2014-15
DIGITAL SIGNAL PROCESSING

PAPER ID : 131602 Roll No. <table border="1" style="display: inline-table; width: 100px; height: 20px;"> <tr> <td> </td><td> </td><td> </td><td> </td><td> </td><td> </td><td> </td><td> </td><td> </td><td> </td> </tr> </table>																			
(Following Paper ID and Roll No. to be filled in your Answer Book)																			

EEC602



Printed Pages : 4

components :

 $\frac{4}{\pi}$ of using bilinear

digital filter with a

with system function

 on with $T=1s$
 $0.5\pi \leq \omega \leq \pi$
 $0.5 \leq \omega \leq 0.2\pi$

v filter to satisfy the

10×2=20

$$\frac{+1}{+1}$$

For the system with

- (c) Calculate the DFT of the sequence $s(n) = \{2, 4, 2, 3\}$.
- (d) State and prove circular convolution property of DFT.
- (e) Explain frequency transformation with L.P.F to HPF conversion formula.
- (f) Draw a transformation matrix of size 5×5 and explain the properties of twiddle factor.

5×4=20

- Attempt any four parts
- (a) Determine $H(z)$ using the impulse invariant technique for the analog system function

$$H(s) = \frac{1}{(s+0.5)(s^2+0.5s+2)}$$

- (b) Realise an FIR filter whose impulse response is $h(n) = \{1, 2, 5, 6, 3, 6, 5, 2, 1\}$ using minimum number of multipliers.
- (c) Determine the response of a discrete-time system for an input signal $x(n) = \{2, 1, 3, 1\}$, if the unit-sample response is of the system is $h(n) = \{1, 2, 2, -1\}$
- (d) Enumerate and explain the properties of DFT.
- (e) Draw the parallel form network structure of the system with transfer function.

$$H(z) = \frac{2z(z+3)}{z^2+0.3z+0.02}$$

- (f) What are the different window functions used for windowing? Explain the effects of using different window functions for designing FIR filter on the filter response.

2

[Contd...]

3

Attempt any two parts

10×2=20

- (a) Derive and draw the flow graph for DIF FFT algorithm for $N=8$.
- (b) Calculate the circular convolution of $s_1(n) = \{1, 2, 1, 2\}$ and $s_2(n) = \{1, 2, 3, 4\}$ using Stockham's method.
- (c) Determine $H(z)$ for a Butterworth filter satisfying the following constraints

$$\begin{aligned} \sqrt{0.5} &\leq |H(e^{j\omega})| \leq 1 & 0 \leq \omega \leq \frac{\pi}{2} \\ |H(e^{j\omega})| &\leq 0.2 & \frac{3\pi}{4} \leq \omega \leq \pi \end{aligned}$$

with $T=1$ sec. Apply impulse invariant transformation

10×2=20

- Attempt any two parts;
- (a) Given $x(n) = 2^n$ and $N=8$ find $X(K)$ using DIT FFT algorithm. Also calculate the computational reduction factor.
- (b) Design a low-pass filter with the following desired frequency response

$$H_d(e^{j\omega}) = \begin{cases} e^{-j2\omega}, & -\frac{\pi}{4} \leq \omega \leq \frac{\pi}{4} \\ 0, & \frac{\pi}{4} < |\omega| < \pi \end{cases}$$

and using window function

$$w(n) = \begin{cases} 1, & 0 \leq n \leq 4 \\ 0, & \text{otherwise} \end{cases}$$

3

[Contd...]

131602]

- (c) Draw the Ladder structure for the system with system function

$$H(z) = \frac{5z^{-3} + 2z^{-2} + 3z^{-1} + 1}{z^{-3} + z^{-2} + z^{-1} + 1}$$

5 Attempt any two parts : 10×2=20

- (a) Design a digital chebyshev filter to satisfy the constraints

$$0.77 \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq 0.2\pi$$

$$|H(e^{j\omega})| \leq 0.1 \quad 0.5\pi \leq \omega \leq \pi$$

Using bilinear transformation with $T=1s$

- (b) Convert the analog filter with system function

$$H(s) = \frac{s+0.1}{(s+0.1)^2 + 9}$$

into digital filter with a

resonant frequency of $\omega_r = \frac{\pi}{4}$ of using bilinear transformation.

- (c) Explain the following phenomenon's :

- (i) Gibbs Oscillations.
- (ii) Frequency Wrapping.

Printed Pages : 4



(Following Paper ID and Roll No. to be filled)

PAPER ID : 131602

Roll No.

B. Tec

(SEM. VI) THEORY EXAM

DIGITAL SIGNAL I

Time : 3Hours]

1 Attempt any four parts

- (a) Draw the block diagram with input $x(n)$ and output

$$w(n) = x(n) + \frac{1}{2}x(n-1)$$

$$y(n) + \frac{1}{4}y(n-1) = w(n)$$

- (b) Obtain the cascade realization system;

$$H(z) = \frac{(1 + \frac{3}{2}z^{-1} + \frac{1}{2}z^{-2})}{(1 + z^{-1} + \frac{1}{4}z^{-2})}$$

131602]

4

[13825]

131602]

1