

Printed Pages: 02

Paper Id: 120710

Sub Code: NEE702/NEN702/EEE042

Roll No.

B.TECH.
(SEM-VII) THEORY EXAMINATION 2018-19
POWER STATION PRACTICE

Time: 3 Hours.

Max. Marks: 100

Note: 1. The question paper contains three sections- A, B & C.
2. Read the instructions carefully in each section

SECTION A

1. Attempt ALL the parts:

[2 × 10=20]

- What is the total power plant installed capability in India?
- Define load factor & penalty factor.
- What do understand by tariff? Give its types.
- Classify hydraulic turbines.
- What are the functions of moderator & coolant in a nuclear power plant??
- What do you understand by economic load dispatch & unit commitment?
- What are the causes of low power factor?
- What is the power output of a ${}^{235}\text{U}$ reactor if it takes 30 days to use of 2 Kg fuel? Given that energy is released per fission is 200 MeV and Avogadro is 6.023×10^{23} per mole.
- What are the advantages of using pulverised coal in thermal power plant?
- What are the different types of generators used in wind energy generation?

SECTION B

2. Attempt any THREE parts:

[10 × 3=30]

- Explain open and closed cycle gas turbine plant along with methods to improve its thermal efficiency. What are its merits and demerits compared to the steam power plants?
- Explain following terms:
(i)Reservoir (ii)Spillways
(iii)Trash Rack (iv) Penstock
- A thermal power plant spends Rs. 25 lakhs in one year on coal consumption. The coal has a calorific value of 5000 Kcal/kg. with cost of Rs. 500/ton. If thermal efficiency is 32% & electrical efficiency is 90%. Find the average load on the power plant.
- A generating station has the following daily load cycle:
Time (hours): 0-6 6-8 8-12 12-14 14-18 18-20 20-24
Load (MW): 45 35 75 20 80 25 50
 - Draw the daily load curve
 - Draw the load duration curve
 - Calculate load factor
 - Calculate plant capacity factor if the capacity of the plant is 120 MW
- Describe the working of open loop MHD system and closed loop MHD system with the block diagram.

SECTION C

3. Attempt any one part:

[10x1=10]

- Draw the layout of thermal power plants & describe the working of it. A 100 MW steam power plant uses a coal of calorific value 6400 kcal/kg. Thermal efficiency of station is 30 % and

MANISH KUMAR JHA | 31-Dec-2018 13:35:01 | 117.55.242.131

- electrical efficiency is 92%. Calculate the coal consumption per hour when the station is delivering to full rated output.
- b. Classify hydro-electric power plants based on (i) water flow regulation (ii) head (iii) load

4. Attempt any one part:**[10x1=10]**

- a. Explain the working of diesel plants with the help of diagram? Give its advantages & disadvantages.
- b. What are the criteria for site selection for nuclear power plant? Explain with a neat sketch the working of a nuclear power plant. Give the classification of nuclear reactors.

5. Attempt any one part:**[10x1=10]**

- a. An electric supply system has a maximum load of 70 MW. The annual expenses of the stem are :

Generation Rs. 85,00,000

Fuel cost Rs. 28,00,000

Transmission Rs. 3,45,000

Distribution Rs. 27,50,000

Repairs etc Rs. 3,00,000

The no. of units generated per year is 600×10^6 kWh. The consumers have an aggregate maximum demand of 75 MW. Evaluate a two-part tariff to be charged from the consumers. Assume that the fixed charges for generation, fuel, transmission, distribution, repair etc are 90%, 15%, 85%, 95% and 50% respectively. Losses in transmission & distribution are 20%.

- b. Explain following:

(i) Substation layout

(ii) Busbar arrangements

6. Attempt any one part:**[10x1=10]**

- a. Explain hydrothermal scheduling with various power system constraints.
- b. What do you understand by economic load scheduling? Explain & derive the expression (i) Neglecting transmission losses (ii) Considering transmission losses

7. Attempt any one part:**[10x1=10]**

- a. Explain generation of electricity by photovoltaic cell & thermoelectric converters for direct conversion of solar energy into electricity.
- b. What is geothermal energy? How it is utilized for the power generation?