

Notations :

- 1.Options shown in green color and with ✓ icon are correct.
- 2.Options shown in red color and with ✗ icon are incorrect.

Question Paper Name: AG: AGRICULTURAL ENGINEERING 31st Jan shift1
Number of Questions: 65
Total Marks: 100.0

Wrong answer for MCQ will result in negative marks, (-1/3) for 1 mark Questions and (-2/3) for 2 marks Questions.

General Aptitude

Number of Questions: 10
Section Marks: 15.0

Q.1 to Q.5 carry 1 mark each & Q.6 to Q.10 carry 2 marks each.

Question Number : 1 Question Type : MCQ

Choose the most appropriate word from the options given below to complete the following sentence.

The principal presented the chief guest with a _____, as token of appreciation.

- (A) momento (B) memento (C) momentum (D) moment

Options :

- 1. ✗ A
- 2. ✓ B
- 3. ✗ C
- 4. ✗ D

Question Number : 2 Question Type : MCQ

Choose the appropriate word/phrase, out of the four options given below, to complete the following sentence:

Frogs _____.

- (A) croak (B) roar (C) hiss (D) patter

Options :

- 1. ✓ A
- 2. ✗ B
- 3. ✗ C
- 4. ✗ D

Question Number : 3 Question Type : MCQ

Choose the word most similar in meaning to the given word:

Educe

(A) Exert

(B) Educate

(C) Extract

(D) Extend

Options :

1. ✗ A
2. ✗ B
3. ✓ C
4. ✗ D

Question Number : 4 Question Type : MCQ

Operators $\square$, $\diamond$ and $\rightarrow$ are defined by: $a \square b = \frac{a-b}{a+b}$; $a \diamond b = \frac{a+b}{a-b}$; $a \rightarrow b = ab$.

Find the value of $(66 \square 6) \rightarrow (66 \diamond 6)$.

(A) -2

(B) -1

(C) 1

(D) 2

Options :

1. ✗ A
2. ✗ B
3. ✓ C
4. ✗ D

Question Number : 5 Question Type : MCQ

If $\log_x (5/7) = -1/3$, then the value of x is

(A) 343/125

(B) 125/343

(C) -25/49

(D) -49/25

Options :

1. ✓ A
2. ✗ B
3. ✗ C
4. ✗ D

Question Number : 6 Question Type : MCQ

The following question presents a sentence, part of which is underlined. Beneath the sentence you find four ways of phrasing the underlined part. Following the requirements of the standard written English, select the answer that produces the most effective sentence.

Tuberculosis, together with its effects, ranks one of the leading causes of death in India.

(A) ranks as one of the leading causes of death

(B) rank as one of the leading causes of death

(C) has the rank of one of the leading causes of death

(D) are one of the leading causes of death

1. ☒ A
2. ☐ B
3. ☐ C
4. ☐ D

Question Number : 7 Question Type : MCQ

Read the following paragraph and choose the correct statement.

Climate change has reduced human security and threatened human well being. An ignored reality of human progress is that human security largely depends upon environmental security. But on the contrary, human progress seems contradictory to environmental security. To keep up both at the required level is a challenge to be addressed by one and all. One of the ways to curb the climate change may be suitable scientific innovations, while the other may be the Gandhian perspective on small scale progress with focus on sustainability.


- (A) Human progress and security are positively associated with environmental security.
(B) Human progress is contradictory to environmental security.
(C) Human security is contradictory to environmental security.
(D) Human progress depends upon environmental security.

Options :

1. ☐ A
2. ☒ B
3. ☐ C
4. ☐ D

Question Number : 8 Question Type : NAT

Fill in the missing value



Correct Answer:

3

Question Number : 9 Question Type : MCQ

A cube of side 3 unit is formed using a set of smaller cubes of side 1 unit. Find the proportion of the number of faces of the smaller cubes visible to those which are NOT visible.

- (A) 1 : 4 (B) 1 : 3 (C) 1 : 2 (D) 2 : 3

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 10 Question Type : MCQ

Humpty Dumpty sits on a wall every day while having lunch. The wall sometimes breaks. A person sitting on the wall falls if the wall breaks.

Which one of the statements below is logically valid and can be inferred from the above sentences?

- (A) Humpty Dumpty always falls while having lunch
(B) Humpty Dumpty does not fall sometimes while having lunch
(C) Humpty Dumpty never falls during dinner
(D) When Humpty Dumpty does not sit on the wall, the wall does not break

Options :

1. ✖ A
2. ✔ B
3. ✖ C
4. ✖ D

Agricultural Engineering

Number of Questions: 55
Section Marks: 85.0

Q.11 to Q.35 carry 1 mark each & Q.36 to Q.65 carry 2 marks each.

Question Number : 11 Question Type : MCQ

The series represented by $a_n = \frac{n^2 - 2n}{3n^2 + n}$ is

- (A) convergent (B) divergent
(C) asymptotic (D) oscillatory

Options :

1. ✔ A
2. ✖ B
3. ✖ C
4. ✖ D

Question Number : 12 Question Type : MCQ

Inverse of the matrix $\begin{bmatrix} 3 & 3 \\ 1 & 4 \end{bmatrix}$ is

- (A) $\begin{bmatrix} 0.1 & -0.4 \\ -0.3 & 0.2 \end{bmatrix}$ (B) $\begin{bmatrix} 0.3 & -0.2 \\ -0.1 & 0.4 \end{bmatrix}$ (C) $\begin{bmatrix} 0.3 & -0.1 \\ -0.2 & 0.4 \end{bmatrix}$ (D) $\begin{bmatrix} 0.4 & -0.2 \\ -0.1 & 0.3 \end{bmatrix}$

Options :

1. ✗ A
2. ✗ B
3. ✗ C
4. ✓ D

Question Number : 13 Question Type : NAT

The distance PQ between two position vectors $\vec{P} = -2\hat{i} + 3\hat{j} + 4\hat{k}$ and $\vec{Q} = 4\hat{i} + 5\hat{j} + 7\hat{k}$ is _____.

Correct Answer :

7

Question Number : 14 Question Type : MCQ

The incorrect statement from the following is

- (A) The peak runoff from an agricultural watershed is generally less than that from an urban watershed of the same area
 (B) The horizontal hydraulic conductivity of soil is less than its vertical hydraulic conductivity
 (C) The magnitude of a 75-year flood is less than that of a 100-year flood
 (D) The rating curve due to an unsteady flood event forms a loop

Options :

1. ✗ A
2. ✓ B
3. ✗ C
4. ✗ D

Question Number : 15 Question Type : MCQ

If x be the highest mean monthly precipitation and y be the mean annual precipitation, then the 'rainfall aggressiveness' to soil erosion is

- (A) $\frac{x^2}{y}$ (B) $\frac{x}{y^2}$ (C) $\frac{x^2}{y^2}$ (D) $\frac{y^2}{x}$

Options :

1. ✓ A
2. ✗ B
3. ✗ C
4. ✗ D

Question Number : 16 Question Type : MCQ

Discharge through an irrigation outlet is independent of the water levels in the distributary and water courses in case of

- (A) non-modular outlet
- (B) semi-modular outlet
- (C) Kennedy's gauge outlet
- (D) Gibb's module outlet

Options :

- 1. ✖ A
- 2. ✖ B
- 3. ✖ C
- 4. ✔ D

Question Number : 17 Question Type : MCQ

The USDA classification of irrigation water with regard to alkali and salinity hazards is based on

- (A) Exchangeable sodium percentage and pH
- (B) Electrical conductivity and Sodium adsorption ratio
- (C) Electrical conductivity and pH
- (D) Sodium percentage and pH

Options :

- 1. ✖ A
- 2. ✔ B
- 3. ✖ C
- 4. ✖ D

Question Number : 18 Question Type : NAT

A steady discharge of $60 \text{ m}^3 \text{ s}^{-1}$ is passing through a trapezoidal irrigation channel with a bottom width of 5 m, bed slope of 0.01% and Manning's roughness coefficient of 0.025. The conveyance of the channel in $\text{m}^3 \text{ s}^{-1}$ is_____.

Correct Answer :

6000

Question Number : 19 Question Type : MCQ

Dupuit-Forchheimer assumptions are used for analyzing groundwater flow in

- (A) confined aquifers
- (B) leaky confined aquifers
- (C) unconfined aquifers
- (D) both confined and unconfined aquifers

Options :

- 1. ✖ A
- 2. ✖ B
- 3. ✔ C
- 4. ✖ D

Question Number : 20 Question Type : MCQ

An unsteady flow drawdown pumping test was conducted in a confined aquifer and the drawdown was measured with time in an observation well located at a certain distance away from the pumping well. Using these time-drawdown data, we can determine

- (A) transmissivity only
- (B) storage coefficient only
- (C) specific storage only
- (D) both transmissivity and storage coefficient

Options :

- 1. ✖ A
- 2. ✖ B
- 3. ✖ C
- 4. ✔ D

Question Number : 21 Question Type : MCQ

Mole drain is the most suitable drainage system for

- (A) heavy clay soil
- (B) loamy soil
- (C) sandy soil
- (D) silty soil

Options :

- 1. ✔ A
- 2. ✖ B
- 3. ✖ C
- 4. ✖ D

Question Number : 22 Question Type : MCQ

The efficiency of a cyclone separator can be increased by

- (A) decreasing the size of the particles
- (B) increasing the velocity of inlet air
- (C) reducing the length of the separator
- (D) reducing the diameter of air outlet

Options :

- 1. ✖ A
- 2. ✔ B
- 3. ✖ C
- 4. ✖ D

Question Number : 23 Question Type : MCQ

The correct statement in respect of rice parboiling process is

- (A) kernel structure becomes soft and it cooks easily
- (B) heat treatment during parboiling preserves some antioxidants
- (C) parboiled rice retains more proteins, vitamins and minerals
- (D) shelling of parboiled rice becomes more difficult

Options :

- 1. ✖ A
- 2. ✖ B
- 3. ✔ C
- 4. ✖ D

Question Number : 24 Question Type : MCQ

In the design of an agitator vessel with model volume V_1 and prototype volume V_2 , the scale-up ratio is given by

- (A) $\frac{V_2}{V_1}$ (B) $\left(\frac{V_2}{V_1}\right)^{1/2}$ (C) $\left(\frac{V_2}{V_1}\right)^{1/4}$ (D) $\left(\frac{V_2}{V_1}\right)^{1/3}$

Options :

1. ✖ A
2. ✖ B
3. ✖ C
4. ✔ D

Question Number : 25 Question Type : NAT

The wall of a cold storage is made up of four layers; concrete, brick, cardboard and paint with respective thickness of 5, 60, 8 and 1 mm, and their corresponding thermal conductivities are 0.8, 0.7, 0.04 and 0.15 W m⁻¹ K⁻¹. The overall resistance of the wall to conduction heat transfer in m² K W⁻¹ is _____.

Correct Answer :

0.29 to 0.31

Question Number : 26 Question Type : NAT

Two very large parallel walls (gray bodies) facing each other have emissivities of 0.5 and 0.7. The view factor between these two walls is_____.

Correct Answer:

0.40 to 0.42

Question Number : 27 Question Type : NAT

In a counter-current flow double pipe heat exchanger (DPHE), temperature difference between the hot and cold liquids at all positions is held constant at C. If the effectiveness of the heat exchanger is 0.65 and heat capacity ratio of hot and cold liquids is 1, the number of transfer units (NTU) is _____.

Correct Answer:

1.85 to 1.90

Question Number : 28 Question Type : NAT

The values of C and n for raisin are 1.283×10^{-4} K⁻¹ and 1.02, respectively in the Henderson equation. The equilibrium moisture content of raisin in percent dry basis corresponding to the air with 70% relative humidity at 40 °C is _____.

Correct Answer :

26 to 30

Question Number : 29 Question Type : MCQ

A power operated chaff cutter with two knives is rotating at 600 rpm. It has a conveyor type feeding mechanism which operates at a speed of 0.6 m s^{-1} . The theoretical chaff length in mm is

- (A) 20 (B) 30 (C) 60 (D) 90

Options :

1. ✖ A
2. ✔ B
3. ✖ C
4. ✖ D

Question Number : 30 Question Type : NAT

The conversion efficiency of a solar cell is 12% . For a maximum power output of $9 \times 10^{-3} \text{ W}$ at an incident solar radiation of 250 Wm^{-2} , the required surface area of the solar cell in mm^2 will be _____.

Correct Answer:

300

Question Number : 31 Question Type : MCQ

The non-combustible constituents of the producer gas are

- (A) Carbon monoxide and Hydrogen (B) Hydrogen and Methane
(C) Nitrogen and Carbon dioxide (D) Carbon monoxide and Nitrogen

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 32 Question Type : MCQ

The grain to straw ratio of wheat crop is 1.5 : 1. The output capacity and cleaning efficiency of a thresher at an optimal operating condition are 500 kg h^{-1} and 99%, respectively. If the grain recovery at main grain outlet is 100%, the throughput capacity in kg h^{-1} will be

- (A) 758 (B) 825 (C) 1238 (D) 1320

Options :

1. ✖ A
2. ✔ B
3. ✖ C

Question Number : 33 Question Type : NAT

The brake power of a six-cylinder, four-stroke diesel engine running at 3000 rpm is 125 kW. Its brake specific fuel consumption is $200 \text{ g kW}^{-1} \text{ h}^{-1}$. Assuming specific gravity of fuel as 0.85, the volume of fuel to be injected per cycle per cylinder in *ml* is _____.

Correct Answer :

0.05 to 0.06

Question Number : 34 Question Type : NAT

For a reference sound pressure of $2 \times 10^{-5} \text{ N m}^{-2}$, the sound level measured at the operator's workspace of a tractor was 80 dB. If the RMS sound pressure is increased by eight times, the resulting sound pressure level in dB, will be _____.

Correct Answer :

98.0 to 98.2

Question Number : 35 Question Type : MCQ

The connecting rod of an internal combustion engine is subjected to

- (A) compression only (B) tension only
(C) both compression and tension (D) torsion only

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 36 Question Type : NAT


Values of the function $y = \frac{1}{1+x^2}$ are $y(0) = 1$; $y(1) = 0.5$; $y(2) = 0.2$; $y(3) = 0.1$; $y(4) = 0.0588$; $y(5) = 0.0385$; $y(6) = 0.027$. Using Simpson's one-third rule, the value of the integral $\int_0^6 \frac{dx}{1+x^2}$ is _____.

Correct Answer:

1.35 to 1.40

Question Number : 37 Question Type : MCQ www.FirstRanker.com

Daily sales figures for a week are shown in the bar chart given below. The mean daily sales and the standard deviation of the sample mean (integer value) are _____ and _____, respectively.



(A) 3571, 1718

(B) 3715, 1915

(C) 3571, 1178

(D) 3715, 1591

Options :

1. ✓ A

2. ✗ B

3. ✗ C

4. ✗ D

Question Number : 38 Question Type : NAT

A coin is tossed ten times. The probability of getting five heads and five tails is _____.

Correct Answer :

0.23 to 0.26

Question Number : 39 Question Type : MCQ

The particular solution to the first order differential equation $\frac{dy}{dx} = x - e^{-x}$ for $y(0) = -1$ is

(A) $2x^2 + e^{-x} - 2$ (B) $2x^2 + e^{-x} + \frac{1}{2}$ (C) $\frac{x^2}{2} - e^{-x} + \frac{1}{2}$ (D) $\frac{x^2}{2} + e^{-x} - 2$

Options :

1. ✗ A

2. ✗ B

3. ✗ C

4. ✓ D

Question Number : 40 Question Type : MCQ

The value of $\int_0^{\pi/2} \sin^3 x \, dx$ is

- (A) 0 (B) $\frac{1}{3}$ (C) $\frac{2}{3}$ (D) 1

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 41 Question Type : MCQ

Two irrigation channels are designed in the same type of alluvial soil having the channel bed slopes of 1.52×10^{-4} and 1.6×10^{-4} , respectively. If the design discharge of the first channel, using Lacey's regime theory, is $30 \, \text{m}^3 \, \text{s}^{-1}$, then the design discharge of the second channel in $\text{m}^3 \, \text{s}^{-1}$ will be

- (A) 22.05 (B) 29.74 (C) 30.26 (D) 40.81

Options :

1. ✔ A
2. ✖ B
3. ✖ C
4. ✖ D

Question Number : 42 Question Type : NAT

A catchment of 720 ha area has 25-year mean rainfall intensity of $100 \, \text{mm} \, \text{h}^{-1}$ occurring for a duration equal to its time of concentration. During a storm event, the catchment received a total of 7.5 cm design rainfall for 6 hours. Assuming ϕ -index of $0.25 \, \text{cm} \, \text{h}^{-1}$ and runoff coefficient of 0.6, the peak ordinate of the 6-h unit hydrograph in $\text{m}^3 \, \text{s}^{-1}$ will be _____.

Correct Answer:

20

Question Number : 43 Question Type : MCQ

A Cipolletti weir has the crest length of 1.2 m and a crest water level of 0.5 m. The average approach velocity of water in $\text{m} \, \text{s}^{-1}$ on the crest is

- (A) 0.49 (B) 1.18 (C) 1.19 (D) 1.32

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 44 Question Type : MCQ www.FirstRanker.com

Match the following items between **Column-I** and **Column-II** with the most appropriate combinations.

Column-I**Column-II**

- i) Direct runoff
- ii) Peak runoff
- iii) Tensiometer
- iv) Isoerodent map
- v) Isopluvial map
- vi) Zone of saturation

- 1) T-year rainfall depth
- 2) Curve Number
- 3) Aquifer
- 4) Rational formula
- 5) 30-minute rainfall intensity
- 6) Field capacity

(A) i-4, ii-2, iii-6, iv-5, v-1, vi-3

(B) i-2, ii-4, iii-6, iv-5, v-1, vi-3

(C) i-4, ii-2, iii-6, iv-1, v-5, vi-3

(D) i-2, ii-4, iii-6, iv-1, v-5, vi-3

Options :

- 1. ✖ A
- 2. ✔ B
- 3. ✖ C
- 4. ✖ D

Question Number : 45 Question Type : NAT

An unconfined aquifer covering an area of 50 ha has a hydraulic conductivity of 20 m day^{-1} and specific yield of 12%. After a significant rainfall event, the water table rises from 17 m to 14.5 m below the ground level. Assuming no abstraction and outflow of groundwater during the recharge period, the amount of groundwater recharge contributed by the rainfall in m^3 is _____.

Correct Answer:

150000

Question Number : 46 Question Type : NAT

If an irrigation water source has the concentrations of Na^+ , Ca^{++} and Mg^{++} as 28, 10 and 5 milliequivalents per litre, respectively, then the Sodium adsorption ratio of this water is _____.

Correct Answer:

10.2 to 10.4

Question Number : 47 Question Type : NAT

In a canal command, maize crop is grown in an area of 30 ha. The crop evapotranspiration (ET_c) of maize is 840 mm per season and the effective rainfall during growing season is 20 mm. It is irrigated with water having salinity of 1.1 dS m^{-1} by a surface irrigation method. If the leaching efficiency of the field soil is 0.8 and the average soil salinity tolerated by the maize crop for 100% yield is 1.7 dS m^{-1} , the depth of irrigation water in mm per season required to meet the seasonal ET_c and leaching requirement will be _____.

Correct Answer :

1000 to 1013

Question Number : 48 Question Type : NAT

The depth of the impounded water in a 72 m long earthen dam is 6.2 m, while the tail water is 2.2 m deep. The hydraulic conductivity of the isotropic and homogeneous soil-fill of the dam is 0.53 m day^{-1} . Flow net method is used to estimate seepage wherein the number of flow channels is 6 and the number of potential drops is 21. The seepage rate through the dam in $\text{m}^3 \text{ day}^{-1}$ is _____.

Correct Answer:

43.50 to 43.70

Question Number : 49 Question Type : MCQ

A horizontal screw conveyor of 2.4 m length conveys wheat grain of bulk density 680 kg m^{-3} and materials factor 1.2. The screw diameter, shaft diameter and pitch of the screw are 0.5, 0.15 and 0.4 m, respectively. If the screw is completely filled with grains and rotates at 60 rpm, the capacity of the screw conveyor in $\text{m}^3 \text{ h}^{-1}$ and the actual power required in hp (approximately) are _____ and _____, respectively.

(A) 257, 2.8

(B) 258, 2.5

(C) 275, 1.9

(D) 396, 2.9

Options :

1. ✓ A

2. ✗ B

3. ✗ C

4. ✗ D

Question Number : 50 Question Type : NAT

A suspension contains 3.6×10^5 spores of *C. botulinum* having a D-value of 1.5 minute at 121.1°C and 8.5×10^6 spores of *B. subtilis* having a D-value of 0.9 minute at the same temperature. The suspension is heated at a constant temperature of 121.1°C . The heating time needed in minutes for the suspension to obtain a survival probability of 10^{-3} for the most heat resistant organism in it is _____.

Correct Answer :

12 to 14

Question Number : 51 Question Type : MCQ

Match the following items between **Column-I** and **Column-II** with the most appropriate combinations.

Column-I

- 1) Microwave dryer
- 2) Spray dryer
- 3) Freeze dryer
- 4) Drum dryer

Column-II

- P) Cyclone separation
- Q) Sublimation of water
- R) Dielectric drying
- S) Drying of fruit pulp

(A) 1-Q, 2-S, 3-R, 4-P

(C) 1-R, 2-S, 3-Q, 4-P

(B) 1-R, 2-P, 3-Q, 4-S

(D) 1-Q, 2-S, 3-P, 4-R

Options :

1. ✖ A

2. ✔ B

3. ✖ C

4. ✖ D

Question Number : 52 Question Type : NAT

A ball mill of 1.8 m diameter is loaded with steel balls each having a diameter of 6 cm. The rotational speed of the ball is kept at 75% of the critical speed. The operational speed of the ball mill in rpm is _____.

Correct Answer :

23 to 25

Question Number : 53 Question Type : NAT

A fat globule of 1.5 μm diameter is rising up in a stagnant skim milk medium of 1005 kg m^{-3} density and 1.5 cP viscosity. If the density of the fat globule is 915 kg m^{-3} , the steady rising velocity of the globule in $\mu\text{m s}^{-1}$ is _____.

Correct Answer :

0.072 to 0.076

Question Number : 54 Question Type : NAT

Two kg mass of air at 20 °C with 0.023 kg water vapour per kg dry air is mixed with 3 kg mass of air at 20 °C with 0.008 kg water vapour per kg dry air to produce 5 kg mass of air at 60% relative humidity at 28 °C. Assume all the streams are at normal atmospheric pressure (101.325 kPa). The saturation vapour pressure of water in kPa at 28 °C is _____.

Correct Answer:

3.65 to 3.75

Question Number : 55 Question Type : MCQ

In a cascade refrigeration system, the COPs of the cooling cycle and cascade are 3.7 and 4.2, respectively. If tonnage (1 TR = 3.52 kW) of the cooling cycle is 15 and the cascade removes 70% of the total heat rejected in the liquid receiver of the cooling cycle, then the powers required by the cooling and cascade compressors in hp are _____ and _____, respectively.

- (A) 67.07, 46.95 (B) 52.08, 39.35 (C) 19.13, 14.99 (D) 14.27, 11.18

Options :

1. ✖ A
2. ✖ B
3. ✔ C
4. ✖ D

Question Number : 56 Question Type : NAT

A single effect long-tube evaporator has ten tubes each of 2.5 cm diameter and 6 m length. It concentrates pineapple juice from 18 °Brix to 23 °Brix. The feed rate into the evaporator is 557 kg h⁻¹ at the boiling point of 70 °C (latent heat of vapourization = 2333.82 kJ kg⁻¹). Neglecting boiling point rise, the overall heat transfer coefficient in W m⁻² K⁻¹ for 12 °C temperature gradient across the tube walls is _____.

Correct Answer :

1375 to 1395

Question Number : 57 Question Type : NAT

In a plate freezer, the plate temperature is maintained at -25 °C. Latent heat of crystallization is 335 kJ kg⁻¹, and the thermal conductivity and density of frozen meat are 1.25 W m⁻¹ K⁻¹ and 1060 kg m⁻³, respectively. Assuming freezing point of deboned meat at 85% water content on wet basis to be 0 °C, the freezing time in minutes for 2 cm thick block of meat, kept between a pair of freezing plates, is _____.

Correct Answer :

3.8 to 4.2

The horizontal component of soil forces acting on the front gang of a right hand offset disc harrow in the directions parallel and perpendicular to the direction of motion are 8 kN and 3 kN, respectively. The corresponding forces on the rear gang are 6 kN and 7 kN, respectively. If the horizontal component of pull acts towards the left of the direction of motion, its magnitude in kN will be _____.

Correct Answer :

14.5 to 14.6

Question Number : 59 Question Type : MCQ

A two-wheel drive tractor is operating a mould board plough at an average speed of 4 km h^{-1} . The draft and the rear axle torque are found to be 30 kN and 25 kN m, respectively. If the rolling radius of traction wheel is 0.7 m and the wheel slip is 20%, the tractive efficiency in percent will be

- (A) 67.19 (B) 46.71 (C) 72.87 (D) 84.00

Options :

1. ✓ A
2. ✗ B
3. ✗ C
4. ✗ D

Question Number : 60 Question Type : NAT

A power operated hydraulic sprayer operating at a pressure of 1.4 MPa has a boom with 11 nozzles spaced at 0.3 m interval. The input power of the pump is 1.5 kW and its mechanical efficiency is 75%. If the nozzle diameter and the discharge coefficient are 2.4 mm and 0.5, respectively, the average jet velocity of the nozzles in m s^{-1} is _____.

Correct Answer:

32.2 to 32.4

Question Number : 61 Question Type : NAT

A propeller type wind turbine of 8 m diameter generates 4 kW electrical power. If the overall efficiency of power generation system is 32% and the density of air is 1.2 kg m^{-3} , the average wind speed in m s^{-1} is _____.

Correct Answer :

7.4 to 7.5

Question Number : 62 Question Type : MCQ

www.FirstRanker.com

In a reciprocating type mower, the maximum inertia force of 2.2 kN along the pitman occurs at 35° crank angle and 25° pitman angle with the horizontal plane. The crank radius is 50 mm and the equivalent mass at the crankpin is 2.5 kg. If the crank rotates at 600 rpm, the resultant force passing through the crankpin in kN will be

- (A) 2.25 (B) 2.68 (C) 2.98 (D) 3.42

Options :

1. ✗ A
2. ✓ B
3. ✗ C
4. ✗ D

Question Number : 63 Question Type : NAT

A multiple disc clutch is to transmit 15 kW at 750 rpm. The inner and outer radii of the friction surfaces are 60 mm and 100 mm, respectively. The coefficient of friction is 0.1 and the maximum allowable pressure is 350 kPa. Assuming uniform wear, the number of pair of contact surfaces required is _____.

Correct Answer :

3

Question Number : 64 Question Type : MCQ

The speed reductions in the 1st low gear of a tractor gearbox and differential with final drive are 5:1 and 40:1, respectively. For the tractor developing 24 kW power at an engine rpm of 2000 with an overall power transmission efficiency of 80%, the total torque in kN m available at the wheel axle will be

- (A) 22.92 (B) 28.64 (C) 16.54 (D) 18.33

Options :

1. ✗ A
2. ✗ B
3. ✗ C
4. ✓ D

Question Number : 65 Question Type : NAT

A double acting hydraulic cylinder has a bore of 200 mm with a piston rod of 140 mm diameter. The extend speed of the piston is 80 mm s^{-1} . If the flow rate of oil during retraction is same as that of the extending, the retract speed of the piston in mm s^{-1} is _____.

Correct Answer:

156.5 to 157.5

www.FirstRanker.com