

Code No: R1621024

R16

SET - 1

II B. Tech I Semester Regular Examinations, October/November - 2017

ELECTROMAGNETIC FIELDS

(Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)

2. Answer **ALL** the question in **Part-A**

3. Answer any **FOUR** Questions from **Part-B**

~~~~~

**PART -A**

1. a) State Gauss law and list its limitations. (2M)
- b) Differentiate conduction and convection current densities. (2M)
- c) State and explain the Biot-Savart's law. (2M)
- d) Find the expression for Force on a straight and a long current carrying conductor placed in a magnetic field. (3M)
- e) Differentiate self and mutual inductance. (2M)
- f) What is the Faraday's law of induction? What is the significance of the terms transformer e.m.f and generator e.m.f.? (3M)

**PART -B**

2. a) Derive an expression for the Electric field intensity due to a finite length line charge along the Z-axis at an arbitrary point  $Q(x,y,z)$  (7M)
- b) An infinite length of uniform line charge has  $\rho_L = 10\text{pC/m}$  and it lies along the Z-axis. Determine electric field  $E$  at  $(4,3,3)$ . (7M)
3. a) Derive the boundary conditions for conductor to dielectric interface for static electromagnetic fields. (7M)
- b) If the magnetic field is  $H = 0.01/\mu_0 a_x$  A/m, what is the force on a charge of 1.0 pC moving with a velocity of  $10^6 a_x$  m/s. (7M)
4. a) Explain about Oesterd's experiment and its applications. (7M)
- b) Compare the concepts of scalar and vector magnetic potentials. (7M)
5. a) Define Torque. Derive the expression for torque on a current loop placed in a magnetic field. (7M)
- b) A current of 10 A flows in each of two conducting wires parallel to each other. The separation between the wires is 2 cm. Find the force per unit length of one of the wires. (7M)
6. a) Derive an expression for mutual inductance between a straight long wire and a square loop wire in the same plane. (7M)
- b) Calculate the inductance of a solenoid of 2000 turns wound uniformly over a length of 0.5m in a cylindrical paper tube of 0.04m in diameter the medium is air. (7M)

Code No: R1621024

**R16**

**SET - 1**

7. a) Starting from Faraday's law of electromagnetic induction, derive the Maxwell equation  $\nabla \times \mathbf{E} = -\frac{\partial \mathbf{B}}{\partial t}$  (7M)
- b) State and prove the Poynting theorem. (7M)

**R16**

Code No: R1621024

**SET - 2**

**II B. Tech I Semester Regular Examinations, October/November - 2017**

**ELECTROMAGNETIC FIELDS**

(Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

- Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)  
2. Answer **ALL** the question in **Part-A**  
3. Answer any **FOUR** Questions from **Part-B**

**PART -A**

1. a) State Coulomb's law. (2M)
- b) Explain the behavior of conductors in an electric field. (2M)
- c) Define magnetic flux density and write the Maxwell's equation related to it (2M)
- d) A conductor of 6m long, lies along z-direction with a current of 2A. Find the force experienced by the conductor if  $\mathbf{B}=0.08 \mathbf{a}_x$  Tesla. (3M)
- e) Explain the concept of inductance in a toroid. (2M)
- f) Write Maxwell's equation in integral as well as differential forms. (3M)

**PART -B**

2. a) Prove that the electric field intensity is the negative gradient of potential. (7M)
- b) Derive Poisson's and Laplace's equations from the fundamentals. (7M)
3. a) Derive the boundary conditions for dielectric to dielectric interface for static electromagnetic fields. (7M)
- b) Derive an expression for equation of continuity (7M)
4. a) State Ampere's circuital law. Specify the conditions to be met for determining magnetic field strength  $H$ , based on Ampere's circuital law. (7M)
- b) Given  $\mathbf{E}=\mathbf{E}_m \sin(\omega t - \beta z) \mathbf{a}_y$  in free space. Find the  $D$ ,  $B$  and  $H$ . (7M)
5. a) Derive Lorentz force equation and explain its significance (7M)
- b) Derive the expression for Torque on a current loop placed in a magnetic field. (7M)
6. a) Derive the expression for self inductance of solenoid. (7M)
- b) A solenoid of 10 cm in length consists of 1000 turns having the cross section radius of 1 cm. Find the inductance of solenoid. What is the value of current required to maintain a flux of 1 milli-Wb in the toroid. Take  $\mu_r=1500$ . (7M)
7. a) Derive the expression for displacement current density and explain its significance. (7M)
- b) Explain in detail about Poynting vector. (7M)

[www.FirstRanker.com](http://www.FirstRanker.com)

Code No: R1621024

**R16**

**SET - 3**

**II B. Tech I Semester Regular Examinations, October/November - 2017**

**ELECTROMAGNETIC FIELDS**

(Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)

2. Answer **ALL** the question in **Part-A**

3. Answer any **FOUR** Questions from **Part-B**

~~~~~

PART -A

1. a) Define electric field intensity and electric flux density. (2M)
- b) Show that the displacement current in the dielectric of parallel-plate capacitor is equal to the conductor current in its leads. (3M)
- c) Derive the magnetic fields due to a circular loop of conductor. (3M)
- d) Find the expression for force between two straight long and parallel current carrying conductors. (2M)
- e) A solenoid with air core has 1000 turns of wire. Its length is 800 mm and core radius is 60mm. Then find the inductance of it. (2M)
- f) Define Poynting theorem and Pointing vector. (2M)

PART -B

2. a) State Guass law. Explain any two applications of Guass law in detail. (7M)
- b) Determine the electric field intensity due to infinite line charge, at a point perpendicular to its plane and at a gives distance from the line charge from first principle. (7M)
3. a) Derive an expression for capacitance of a parallel plate capacitor containing two dielectrics with the dielectric interface parallel to the conducting plates. (7M)
- b) Find the capacitance of two parallel plates 30cmX30cm separated by 5 mm in air. And also find the energy stored by the capacitor if it is charged to a potential difference of 500 volts. (7M)
4. a) state Ampere's circuital law and explain any two applications of it. (7M)
- b) A circular loop located on $x^2 + y^2 = 9$, $Z = 0$ carries a direct current of 10 A along $\mathbf{a}_\phi$. Determine Hat (0,0,4) and (0,0,-4). (7M)
5. a) Explain the concepts of magnetic dipole and dipole moment in detail. (7M)
- b) In a magnetic flux density of $\mathbf{B} = \mathbf{a}_x + 3\mathbf{a}_y$ Wb/m², a current element $10\mathbf{a}_z$ mA-m is placed. Find the force on the current element. (7M)
6. a) Derive the expression for energy density in a magnetic field. (7M)
- b) Obtain an expression for the self-inductance of a toroid of a circular cross-section, with N closely spaced turns. (7M)

Code No: R1621024

R16

SET - 3

7. a) Derive Maxwell's equations for time varying fields from their basics. (7M)
- b) A conducting circular loop of radius 20 cm lies in the $z=0$ plane in a magnetic field $B = 10 \cos 377t \mathbf{a}_z \text{ mWb/m}^2$. Calculate the induced voltage in the loop. (7M)

Code No: R1621024

R16**SET - 4****II B. Tech I Semester Regular Examinations, October/November - 2017****ELECTROMAGNETIC FIELDS**

(Electrical and Electronics Engineering)

Time: 3 hours

Max. Marks: 70

Note: 1. Question Paper consists of two parts (**Part-A** and **Part-B**)2. Answer **ALL** the question in **Part-A**3. Answer any **FOUR** Questions from **Part-B**

~~~~~

**PART -A**

1. a) What are the applications of Laplace's and Poisson's equations? (2M)
- b) State the boundary conditions between two dielectrics (2M)
- c) State Ampere's circuital law and explain any one of its applications. (3M)
- d) Find the expression for the torque on a current loop placed in a magnetic field. (2M)
- e) A solenoid with 300 turns is 300 mm long and 30 mm in diameter. If the current flowing is 500mA, find the inductance. (2M)
- f) What is the inconsistency in Ampere's law? How it is rectified by Maxwell? (3M)

**PART -B**

2. a) State and explain Gauss law in differential form and also list the limitations of Gauss's law. (7M)
- b) A circular ring of charge with radius 5m lies in  $z = 0$  plane with centre at origin. If the line charge density is 10 nC/m. Find E at the point (0, 0, 6) m. (7M)
3. a) Derive the expressions for energy stored and energy density in a static electric field. (7M)
- b) Find the capacitance of two parallel plates 30cmX30cm separated by 6 mm in air. And also find the energy stored by the capacitor if it is charged to a potential difference of 600 volts. (7M)
4. a) Derive the expression for magnetic field intensity due to a straight current carrying filament. (7M)
- b) Derive Ohm's law in point form and explain (7M)
5. a) Derive the expression for Torque on a current loop placed in a magnetic field. (7M)
- b) A toroid coil of 600 turns has a mean radius of 50cm and radius for the winding of 4cm. Find the value of average self-inductance with an iron core of  $\mu_r=900$ . (7M)
6. a) Derive the expression for mutual inductance between a straight long wire and a square loop wire in the same plane. (7M)
- b) Derive the expression for energy density in a magnetic field. (7M)
7. a) Explain how the concept of displacement current was introduced by Maxwell to account for the production of magnetic field in the empty space. (7M)
- b) Compare Maxwell Equations for free space and sinusoidal variations. (7M)

[www.FirstRanker.com](http://www.FirstRanker.com)